	SCHEDULE OF ITEMS FOR ELECTRICAL WORK AT KUNDAM BRANCH	(RBC)-1) JAE	BALPUR	
S.No	Description of items	Qty	Unit	Rate	Amount
(A)	ELECTRICAL WIRING WORK				
1	Note: Use of Flexible conduits & Elbows in Circuit wiring is not allowed except in exceptional site conditions with the approval of Bank's Engineer / Architect and All wiring laying in the MS/PVC conduit strickle follow IE(Indian Electricity) rules follow in all items of project/ work execution. Proper ferrules, lux, thimble, gland termination to be done in all cabling & wiring from both load/source end. Conduit carrying submain will not carry circuit/point wiring. Similarly conduit carrying circuit wiring will not carry submain/point wiring. Conduit carrying point wiring will not carry submain/circuit wiring.				
	Providing, fixing, testing and commissioning of POINT WIRING of any length				
	for light point/Wall fan point/Exhaust fan point/ Call bell point/ including call bell/ including fan box(if required), 'S' type fan hook etc with 1.5 Sq.mm(P/N/E) PVC 650V/1100V Grade FR insulated copper conductor single core multi strended wire in 16 SWG(Medium Gauge) stove enamelled rigid steel conduit 20mm/25mm with conduit accessories like bend, junction box etc in concealed/surface manner as per site requirment with suitable Modular Switches/Sockets with plate and Metal/PVC box,Scaddle, angle bracket (if required), 3 plate ceiling rose/bulb holder etc. The floor/roof/wall junction box shuold be of MS(heavy duty) box of suitable size and covered with Steel finish Steel cover sheet by screw tight and gasket to avoid water/dust insertion. The item includes Circuit wiring from DB to the switch board with 3x2.5 Sq.MM. The above wiring carried out surface or recess in wall/floor/roof should be cutting by cutter/chiesling, replastering, curing, painting with uniform and smooth finish by specilised workman ship and making the surface neat afterwards complete in all respect as per direction of Bank Engg. (EACH Circuit to take NOT MORE than 7-8 points) The conduit/ Flexible conduit/junction box/metal modular box etc must be joined by gland and check nut at both ends. (each circuit to be controlled by one MCB). The colour code of wire are as under: Phase- Red, Neutral- Black, Earth-Green Make of Material for items of BOQ:- (i) Modular Type Switch/socket/step electronic fan regulator, plate, box, TV/telephone, bulb holder/3 pin ceiling rose with all accessories:- Lergand/ Anchor(Roma)/MK/ Crabtree (ii) MS conduit/PVC conduit with all accessories:- BEC/AKG/NIC/Precision (iii) PVC insulated copper wire(FR) 650V/1100 V grade:- Finolex/RR cable/ Havells				
а	Providing and fixing of point wiring with above specifications. One light point controlled by one switch.	40	Nos.		
b	Providing and fixing of point wiring with same above specifications. Two light points to be controlled by one switch.	15	Nos		
С	Providing and fixing of ceiling fan point controlled as under (i) one 6 amp switch				
d	(ii) one no stepped electronic regulator of two module type. providing and fixing 6 Amps Plug Points with same specs as above and install	6	Nos.		
2	along with same light switchboard 6 AMP. POINTS ON SEPARATE BOARD :	10	Nos		
	Supply,fixing,testing and commissioning of 1 No 6 A Multi Socket with 1No. 6 A switch (Modular type) with cover plate, sheet steel box / PVC modular box etc on surface / concealed manner I/c electrical connections and making good all the damages, painting, cleaning the site etc complete including all accessories as per site requirement and as directed. (Minimum two and Maximum three points are loop with one circuit as mentioned beolw)	10	Nos		
	Page 1				

3	Power Wring (6 / 16 AMP. POWER POINTS)				
	Supply, fixing, testing and commissioning of 1 No 16 A switch & 1 No.six pin				
	6/16 Amp. Multi Socket (Modular Type) with cover plate, sheet steel box etc on surface / concealed manner I/c electrical connections and making good				
	all the damages, painting, cleaning the site etc complete including all				
	accessories as per site requirement and as directed.				
	(Maximum two points are loop with one circuit as mentioned below)				
4	CRECIAL POINTS : / For Committees >	14	Nos		
4	SPECIAL POINTS : (For Computers) Supply, fixing, testing and commissioning of following Modular type switch				
	socket with cover plate, PVC modular box on Surface / sheet steel box in				
	concealed manner I/c electrical connections and making good all the				
	damages, painting, cleaning the site etc complete including all accessories as				
	per site requirement and as directed. 2 Nos. 6 A Switch + 3 Nos. 6 A, 3 pin Socket				
	(Minimum two and Maximum three points are loop with one circuit as				
_	mentioned beolw)	20	Nos		
5	AC/Geyser Point (Single Phase) Supply, Installation, Testing and commissioning of the surface / recess				
	mounting A.C. / GEYSER power point with the followings :				
	Metra Plug and Socket DBs with one Nos 20 Amp SP MCB, 20 Amp plug and				
	socket with complete Enclosur plate and box 1 set i/c electrical connections				
	and making good all the damages, painting, cleaning the site etc complete including all accessories as required as per site requirement and as directed				
	by Bank Engineer.				
	OR Modular 32A DP 1 way switch with plate & box 1 set. + 25A & 10A twin				
	socket	7	Niss		
6	(Only one point is connected with one circuit as mentioned below) AC Point (Three Phase)	7	Nos		
a.	Supply, Installation, Testing and commissioning of the surface / recess				
	mounting A.C. Cassette power point with the followings :				
	Metal enclose Four way with one Nos 32 Amp FP MCB with complete				
	Enclosur plate and box 1 set i/c electrical connections and making good all the damages, painting, cleaning the site etc complete as required as per site				
	requirement and as directed. (Only one point is connected with one circuit as				
	mentioned below)	0	Nos	Nil	
7	CIRCUIT WIRING:				
	Supplying, providing circuit wiring for Power/UPS with following PVC insulated copper conductor single core multi strended wire (HRFR) in				
	mentioned conduit i/c electrical connections in suitable size MS / PVC modular				
	boxes and it laying, fixing, testing and commissioning in suitable size 20/25				
	mm dia,16 SWG (Medium Gauge) thickness rigid MS conduit with conduit accessories like bend/junction box/ fan box etcwith cover plate, sheet steel				
	box/ PVC modular box etc on surface/ concealed manner i/c electrical				
	connections and making goods all the damages, replastering, painting,				
	cleaning the site etc complete as required as per site condition. The				
	floor/roof/wall junction box shuold be of MS(heavy duty) box of suitable size and covered with Steel finish Steel cover sheet by screw tight and gasket to				
	avoid water/dust insertion. The length of circuit upto 30 meter length or less				
	as per site condition/requirment. Make of Material				
	(i) MS conduit/PVC conduit with all accessories:- BEC/AKG/NIC/Precision (ii) PVC insulated copper wire(FR) 650V/1100 V grade:- Finolex/RR cable/				
	Havells				
а	3 X 2.5 sqmm(For UPS Circuit/6 amp Separate Board) in suitable size of				
	16 SWG (MMS) steel conduit as per IS code.	12	Nos		
b	3 X 4.0 sqmm (For AC/Power Circuit) in suitable size of 16 SWG (MMS) steel conduit as per IS code.	15	Nos		
8	UPS OUTGOING & OTHER WIRING, As Per Requirment.	13	1403		
(a)	3 x 10 Sqmm copper multistreand wire in 25 mm 16 SGW (MMS) steel				
	conduit.(UPS INPUT DB TO UPS)	0	R.Mtr	Nil	

(b)	3 X 1.5 Sqmm copper multistreand wire in suitable size of 16 SWG (MMS) steel conduit.	5	R.Mtr		
(c)	3 X 2.5 Sqmm copper multistreand wire in suitable size of 16 SWG (MMS) steel conduit.	5			
(d)	3 X 4 Sqmm copper multistreand wire in suitable size of 16 SWG (MMS) steel conduit.	5			
(e)	5 X 4 Sqmm. Copper multistrend wire in suitable size of 16 SWG (MMS) steel conduit (For Cassettee AC)		R.Mtr	Nil	
(f)	3 X 6 Sqmm copper multistreand wire in suitable size of 16 SWG (MMS) steel conduit.		R.Mtr		
9	DISTRIBUTION BOARDS				
	All MCB to be "C" series				
	Supply, installation, Testing and commissioning of the surface/recess mounting following ways MCB DB's 230/415 Volts with tinned copper busbar, neutral bar, earth bar, din bar detachable gland plate, interconnection and making good all the damages, painting, cleaning the site etc complete as required as per site requirement. All MCCB has braking capacity is 25KA and ALL MCB/ELCB has breaking capacity has 10 KA.				
а	Supplying, installation, testing and commissioning of indoor type, sectionalised, compartmentalized, MV Panel board of suitable size fabricated from CRCA sheet of 2 mm thick for frame work,enclosure and doors, 3 mm thick for gland plates with stiffers where required, having vibration free structure chemically treated with seven tank process before painting for surface treatment and powder coated,with aluminum busbar with DMC / SMC busbar supports suitable for 3 Phase 415 V 50 Hz AC supply i/c providing and fixing the following switchgear mounted thereon complete with gaskets and interconnections, connection as per specification complete as required. (The board shall be dust & vermin proof with suitable degree of IP protection) NOTE: All switchgears les shall be equal to 100% lcu. Sheet 14 swg: panel sides,upper,lower,and Ft.doors Sheet 16 swg: back side and compartments. Glande plates: 3 mm thick. Cable entry: Provision at bottom and upper sides. The above panel belongs following as under: A. 4 Nos. 200 Amp. Electrolytic grade Aluminum Bus Bars insulated with colored Heat Shrinkable PVC Sleeves & duly supported on SMC/DMC molded supports with Antitracking barriers. B.INCOMING SWITCHGEARS: (RYB LED Indicators for Both Main/DG) (i) 1 No. FP. 125 A., 25 KA MCCB with thermal magnetic trip unit with 4 nos, 200 amp bus bar with indicator. C. OUTGOING SWITCHGEARS: (i) 160 amp onload changeover for DG supply with 200 amp bus bar with indicator (Note:- Before Placing the Panel order, firstly it Passed by The Bank Authority, otherwise it will not considered)		Nos		
b	Supply & Installation of SDP(Surge Protector Devicve) for general protection of main Distribution Board Legrad Make Cat No. 412247 (3P+N), 40 KA, T2-Imax 40KA/pole with complete wiring.	1	Noo		
d	Providing and fixing 6 way TPN double door DB for LIGHT /POWER POINTS with 63 Amp TPN , controlling 18 Nos. 10/16 Amps SPMCBs. & Complete.	1 1	Nos Nos		
d	Providing and fixing 4 way TPN double door DB for AC POINTS with 63 Amp TPN , controlling 32 amp SP MCB 12 Nos & Complete.	1	Nos		
е	Providing and fixing (12) way SPDB double door type For UPS points with 1x32 Amps DP, controlling 10 NO.10 A./16 AMP SPMCB	1	Nos.		
f)	Providing and fixing (8) way SPDB double door type For Light DB only for Emergency Lights like glow sign etc with 1x32 Amps DP, controlling 6 NO.10 A./16 AMP SPMCB		Nos.		
-		_			

g	Providing and fixing (4) way TPN double door type For UPS INPUT with 1x63 Amps TPNand 63 amp DP MCB- 3 Nos & 3 Nos, 32 amp SP MCB complete(SERVER ROOM AC CONNECTED WITH THIS DB)	1	Nos.	
h	Providing and fixing of Kit Kat Rewirable Porcelian fuse carrier & base with wooden frame of 200 amp/415 Volt near meter box	1	Set	
10	CABLES			
	Supplying, unloading, storage, laying, testing and commissioning of PVC/XLPE insulated (Heavy Duty) Al/Cu conductor armoured cable suitable for working voltage upto and including 1100 V grade, laid and tied on existing overhead cable trays, or laid and tied over MS supports in masonry trenches with copper/al cable lugs, single compression brass cable glands, tapping, crimping etc. as required and all cables run with double run(2 No.) of GI wire of 8 SWG size. The size of cables are as under:-Make of Material:- (i) PVC/XLPC Armoured cable:- Finolex, Havells, RR cable, CCI(Cable Corp. of India) (ii) Cable Termination:- Dowells, Comet			
а	3.5 X 35 Sq.mm XLPE. Al. armoured Cable(AC VTPN & BUS BARS)		N 44 m	
a b	4X 25 Sq.mm XLPE.Al.armoured Cable (POWER)	60	Mtr	
	4X 16 Sq.mm XLPE.Al.armoured Cable (UPS INPUT Supply)/ LIGHT	20	Mtr	
С	SUPPLY	40	Mtr	
11	EARTHING	70	10161	
(i)	COPPER PLATE EARTH STATION: Preparation of the Plate Earth Station:(As per IS:3043) (a) Excavation of hard rocky earth, soft murrum, hard murrum etc and back filling with black cotton soil for the earth station, the earth pit size is 1000 mm X 1000 mm X 2500 mm. (b) Supply and fixing of Copper Plate of Size 600 mm X 600 mm X 3.0 mm thick. (c) Fixing of 50 mm X 6 mm, 3 Mtrs copper strips from Copper Plate to earth terminal including brazing/welding at plate etc. (d) Supply and laying in position 19 mm, 2 Mtrs G.I "B" Class pipe for watering with reducer/funnel with mesh. (e) Supply and Fixing of the following in the earth station. (i) 75 Kg. Charcoal. (ii) 15 Kg. Original Salt. (iii) Black Cotton soil of adequate amount. (f) Construction of earth pit chamber including necessary brick work concrete, plastering, S/F of C.I Cover of size 12" X 12" complete as per site requirment.	2	Nos	
(ii)	G.I.PLATE EARTH STATION: Preparation of the Plate Earth Station: (as per IS:3043) (a) Excavation of rocky earth, soft murrum, hard murrum etc and back filling with black cotton soil for the earth station, the earth pit size is 1000 mm x 1000 mm x 2500 mm deep. (b) S/F of G.I. plate of size 600 x 600 x 6.0 mm thick. (c) S/F fixing 50 mm x 6 mm, 3 mtrs G.I, strips from G.I.plate to earth terminal including brazing / welding at plate etc. (d) Supplying and laying in position 19 mm, 2 mtrs G.I. 'B' class pipe for watering.with reducer/funnel with mesh. (e) S/F of the following in the earth station. 75 Kg. Charcoal, 15 Kg. Original Salt. and Black Cotton soil of adequate amount. (f) Construction of earth pit chamber including necessary brick work concrete, plastering, S/F of C.I. Cover of size 12" x 12" complete as per site req.and marking its value and identification etc. Providing and fixing Copper/GI strip as per specification compete including connection to earth electrode revetting/sweating/soldering, burying 15 cms below in all types of soil/rocks etc complete as requiued. .(a) Copper Strip 25 X 5 mm	3	Nos	
L	Page 4	10	Mtr.	 <u> </u>
	F 855 't			

	(b) G.I.Strip 25 X 5 mm	20	Mtr		
(iv)	Supply and laying of 10 Sq.mm 650V/1100 V PVC grade insulated copper				
	wire in 15 mm G.I. Pipe ISI grade including all accessories complete as				
	required.(Dedicated Earthing for UPS output DB only)	10	Mtr.		
12	OCCUPANCY SENSORS:-				
	Supply, installation , testing and commissioning of occupancy sensor				
	surface/recess mounted as per site condition complete with all				
	wiring/conduit/Switch etc complete in all respect as per site condition as				
	required Honeywell Make K5015/16, Siemens/Johnson Control	2	Nos		
13	OR Equivalent as per Bank's approved. TELEPHONE POINT		1105		
13					
	Supplying, Installation, testing and commissioning of the telephone point with the followings				
(i)	Two pair, 0.61 mm dla. telephone cable tinned copper conductor, P.V.C.				
(.)	insulated and sheathed, fire retarding, anti termite, colour coded twisted pairs				
	and rip cord, Double outlet The length of telephone cable upto 35 meter length				
	or less as per site condition with shutter modular type Telephone Outlets (RJ				
	— 11) wth suitable size MS / PVC modular boxes and it laying, fixing, testing				
	and commissioning in suitable size 20/25 mm dia,16 SWG (Medium Gauge)				
	thickness rigid PVC conduit with conduit accessories like bend/junction				
	box/cover plate/sheet steel/PVC box on surface/ concealed manner i/c				
	electrical connections and making goods all the damages,replastering,				
	painting, cleaning the site etc complete as required as per site condition. The				
	floor/roof/wall junction box shuold be of MS(heavy duty) box of suitable size				
	and covered with Steel finish Steel cover sheet by screw tight and gasket to				
	avoid water/dust insertion.				
	Make of Material:- Delton/Finolex/RR cable	6	Nos		
(ii)	Supplying and fixing of krone telephone tag block on surface/ recess mounted				
	with its accessories suitable for the multi core telephone cable and shall				
	accommodate tin-plated phosphor bronze connectors, the connectors shall				
	splice unskinned cables up to 0.61 mm dia and shall be terminate both				
	incoming and out going lines, the tag blocks shall be mounted inside, water				
	proof box and locking arrangement and shall be fully accessible.				
	(A) 20 Pair tag block				
4.4	DATA CARLING FOR LAN	1	Nos		
14	DATA CABLING FOR LAN				
а	Providing, fixing, testing and commissioning of all nodes of four pair UTP CAT				
	6 LAN cables length upto 30 meter length or less as per site conditionin				
	suitable size 20/25 mm dia, 16 SWG wall thickness rigid PVC conduit with				
	conduit accessories like bend/junction box/ fan box etc on surface/recessed manner and making good all the damages, painting, cleaning the site etc				
	complete as required as per site condition and as directed as required.				
	Junction box shuld be covered with Stainless steel plate with screw with				
	gasket for protection of water/dust. Providing, fixing, testing and				
	commissioning of modular type Information Outlets with suitable size of				
	MS/PVC modular boxes complete, all accessories with insulation				
	displacement connectors etc suitable for CAT 6 UTP cabling with RJ-45				
	socket with testing and commissioning of STP cabling with scanner for all the				
	nodes/switches/jack panel complete (Each point/circuit/cable from both load				
	and source end to be marked with ferrules.)				
	Make of Material:-				
	(i) Data Cable, Cat 6 cable, Switch, Jack panel, Rack, Patch cords & Other				
	accessories:- D-Link, Legrand				
	Design and figure 40/400 Mill. DEC.	15	Nos		
b	Providing and fixing 10/100 Mbps DES series Rack mounted switch) CAT 6				
	suitable for auto-sense the network speed of the connected nodes to run at				
	either 10 /100/1000 Mbps. The pt also auto negotiate between full/ half duplex				
	and cable cross over. 24 RJ 45 10 base-T/100 base - TX Port . 24 ports complete D-Link make	0	Nos.	Nil	
С	Providing and fixing Patch Panels 24 port (100 base TX) CAT 6 patch/jack	U	1105.	INII	
	panel with connector, out lets and necessary connectivity complete as				
	required & (D-Link make) Page 5	1	Nos		
	, , , , , , , , , , , , , , , , , , ,				

RACKS for gig switches, patch panels etc including cooling DUAL fan trays, a 10 Point PDU, Fixed Trays as necessarycomplete. 9 U wall mounted RACK 1 Nos e Providing and fixing of flowing factory fabricated Patch cords. (UTP/CAT 6 complte with connector on both side.)			1	1	ı
9 U wall mounted RACK 9 Providing and fixing of flowing factory fabricated Patch cords. (UTP/CAT 6 comple with connector on both side.) 10 For 1 ML long 11 For 7 ML long 12 For 7 ML long 13 For 7 ML long 14 For 7 ML long 15 For 8 ML long 16 Providing, fixing,testing and commissioning of four pair CAT 6 LAN cable in suitable size of 20/25mm PVC medium gauge 16SWG conduit including all accessories to interconnect the switches from different location. 15 TV POINT:-Supply, installation, testing and commissioning of TV point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect 16 Supply and installation of Vinyl slicker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc. 17 Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entier Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the 18 Ank S Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, chargeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 1 TOTAL. (A) ELECTRICAL WORK 1 TOTAL IN WORDS: 18 LIGHT AND FAN FIXTURES 19 Description of light flan fixture 19 Supply and Installation, Testing and commissioning of the following fittings (equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suilable size of Gliwie to four corner of fittings to the RCC rooftop with suitable size of Gliwie to four corner of fittings to the RCC rooftop with suitable size of Gliwie to four corner of fittings to the RCC rooftop with suitable size of Gliwie to four share as unders. 19 LIED LUMINARES. 2' x2' (FULL GLOW TYPE) 10 LED LUMINA	d				
e Providing and fixing of flowing factory fabricated Patch cords. (UTP/CAT 6 complex with connector on both side.) 1) for 1 Mt. long 1) for 2 Mt. long 1) for 2 Mt. long 1) Providing, fixing, lesting and commissioning of four pair CAT 6 LAN cable in suitable size of 20/25mm PVC medium gauge 165WG conduit including all accessories to interconnect the switches from different location. 100 Mtr 15 TV POINT:-Supply, installation, testing and commissioning of TV point(Modular) with RC-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect to the switches from different location. 10 Nos 16 Supply and installation of Viryl sticker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc. 10 Nos 17 Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entier Electrical work (Power/UPS/Light/DataTelephone/AC etc.) as advised by the Bank's Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 1 sum of 10 to 10			1	Nos	
In In In In In In In In	е	Providing and fixing of flowing factory fabricated Patch cords. (UTP/CAT 6			
ii) for 2 Mt. long 1) Providing, fixing,testing and commissioning of four pair CAT 6 LAN cable in suitable size of 20/25mm PVC medium gauge 16SWG conduit including all accessories to interconnect the switches from different location. 15 TV POINT-Supply, installation, testing and commissioning of TV point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect 16 Supply and installation of Vinyl sticker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc 17 Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entier Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, changevoer, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 1 TOTAL: (A) ELECTRICAL WORK 1 TOTAL: (A) ELECTRICAL WORK 1 TOTAL: NO YAR PIXTURES 2 Description of light fian fixture 3 Supply and installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastener etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2X2 and 4"X1" etc. as per instruction of Bank Eng. (a) LED LUMINARES: 2 x2 (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electronic driver are as under: PHILIPS: GREENLED-DN193B LED-1328-6800 PSU WIRPO: ARRANGE CORD. AND ARRANGE CORD. AND A	i)	for 1 Mt. long	15	Nos.	
Providing, fixing, testing and commissioning of four pair CAT 6 LAN cable in suitable size of 20/25mm PVC medium gauge 16SWG conduit including all accessories to interconnect the switches from different location. TV POINT:-Supply, installation, testing and commissioning of TV point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect TV POINT:-Supply, installation, testing and commissioning of TV point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect TV POINT:-Supply, installation of Vinyl sticker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entire Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of lightfain futures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said TOTAL: (A) ELECTRICAL WORK TOTAL IN WORDS:	ii)	for 2 Mt. long			
suitable size of 20/25mm PVC medium gauge 16SWG conduit including all accessories to interconnect the switches from different location. 15 TV POINT:-Supply, installation, testing and commissionig of TV point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect 16 Supply and installation of Vinyl stocker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc 17 Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entire Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of light/fain fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 10 TOTAL: (A) ELECTRICAL WORK 10 Description of light fain fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC condrop with suitable size of and to four corner of fittings to the RCC condrop with suitable size of and to four corner of fittings to the RCC condrop with suitable size of and to four corner of fittings to the RCC condrop with suitable size of and with the found of Bank's Model No are as under: PHILIPS: RC380B 02 LED 35S-6500 PSU OD WH LED (FULLGLOW) WHRO: ORCCO10RO 38 HPS7 HAVELLS: LHECOLITILITW036 (Edge-Lit) CG: LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Wat, surface mounted circular/square down ligh		· ·	- 10	1400	
15 TV POINT:-Supply, installation, testing and commissioning of TV point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect 16 Supply and installation of Vinyl sticker for on Electrical DBs like, "Switch Off at Night", Switch Off at Night William (Night"), Switch Off at Night William (Night"), Switch Switch Off Casing Capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said to the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said to TOTAL: (A) ELECTRICAL WORK TOTAL IN WORDS: (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of all wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner-leavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:-2 x2' (FULL GLOW TYPE) LED light fittings (600 x600mm) dimension suitable for grid/gyosum ceiling complete with its electronic driver are as under:-PHILIPS:-GRENLED-DN	.,	suitable size of 20/25mm PVC medium gauge 16SWG conduit including all	100	Mtr	
point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit with all accessories complete in all respect 16 Supply and installation of Vinyl sticker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc 17 Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entire Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, changevoer, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 10 TOTAL: (a) ELECTRICAL WORK 10 TOTAL: (a) ELECTRICAL WORK 10 TOTAL: (b) ELECTRICAL WORK 10 LIGHT AND FAN FIXTURES 10 Description of light/fan fixture 11 Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc. complete as per site conditions. All fittings should be hang with suitable size of Gl wire to four comer of fittings to the RCC rooftop with suitable size of anchor fastnered complete as per site conditions. All fittings in false ceiling especially 2"X2" and 4"X1" etc. as per instruction of Bank Eng. (a) LED LUMINARES:- 2" x2" (FULL GLOW TYPE) LED light fittings (600 x600mm) dimension suitable for grid/gypsum ceiling complete with its electronic driver are required per instruction of Bank's Model No are as under:- PHILIPS:- RG380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO-CRCOTORO 38 HPS7 HAVELLS:- LHECDIL7II.1W036 (Edge- Lit) GG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN1938 LED-12S-6500 PSU WIPRO-RISI LED LD 17-121-X	15	TV POINT:-Supply installation testing and commissionia of TV	100	IVILI	
Supply and installation of Vinyl sticker for on Electrical DBs like, "Switch Off at Night", Switch Off For Safety, etc Making & Providing of 3 sets of Asbullt Drawing with coloured print for entier Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said TOTAL: (A) ELECTRICAL WORK TOTAL: NWORDS: (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES: 2' x2' (PULL GLOW TYPE) LED light fittings (600 x600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS: RCS80B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO: CRCO1ORO 38 HP67 HAVELLS: LHECDLITI.1W036 (Edge- Lit) CG: LCTAR3-40-CDL (b) LED DOWNLIGHTER: LED DOWNLIGHTER: SUFFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 14 Nos 15 Watt, recessed mounted circular/square down lighter, 6" dimension with complete its electronic		point(Modular) with RG-6 cable in the Medimum Gauge 1.6 mm PVC Conduit	1	Nos	
Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entier Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said TOTAL: (A) ELECTRICAL WORK TOTAL IN WORDS: (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' x2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electronic driver are as required per instruction of Bank's Model No are as under:-PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HPS7 HAVELLS:- LHECDILTILTW036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:-PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPD IW 015(ENDURA LOW DEPTH) GG:- LC DD-15-CDL, (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are	16				
Electrical work (Power/UPS/Light/Data/Telephone/AC etc.) as advised by the Bank's Authority. Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 1 sum 1	17	Making & Providing of 3 sets of Asbuilt Drawing with coloured print for entier	_		
Banks Authority. 18 Removal and dismentalling of all existing old wiring, switchgears, DBs, changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said 1 TOTAL: (A) ELECTRICAL WORK 1 TOTAL IN WORDS: (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' x2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRC010R0 38 HP57 HAVELLS:- LHECDILT/IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ IW 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER: SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-				Lum	
changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of the premises in any location as per direction of Bank. Payment of whole work should be made after the complete removal and dismentalling of above said TOTAL: (A) ELECTRICAL WORK TOTAL IN WORDS: (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2"X2" and 4"X1" etc. as per instruction of Bank Engg. (a) LED LUMINARES:-2" x2" (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HP57 HAVELLS:- LHECDIL/TIL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter , 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED- DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ IW 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER: SUFFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter , 6" dimension with complete its electronic driver are as under:-			1	sum	
should be made after the complete removal and dismentalling of above said TOTAL:- (A) ELECTRICAL WORK TOTAL IN WORDS:- (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' x2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ TW 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, 14 Nos (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-	18	changeover, main switch, old casing capping, old wooden casing capping, all type of light/fan fixtures and kept them in good condition with in 200 meter of			
TOTAL:- (A) ELECTRICAL WORK TOTAL IN WORDS:- (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of GI wire to four corner of fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' x2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with it selectrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP 2PZ TW 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER: SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-		· · · · · · · · · · · · · · · · · · ·			
TOTAL IN WORDS:- (B) LIGHT AND FAN FIXTURES Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' X2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRC010RO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, 14 Nos (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-		· · · · · · · · · · · · · · · · · · ·	1	sum	
B LIGHT AND FAN FIXTURES		TOTAL:- (A) ELECTRICAL WORK			
Description of light /fan fixture Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' x2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electronic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter , 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter , 6" dimension with complete its electronic driver are as under:-		TOTAL IN WORDS:-			
Supply and Installation, Testing and commissioning of the following fittings / equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' x2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electronic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTES:URFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-	(B)	LIGHT AND FAN FIXTURES			
equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per instruction of Bank Engg. (a) LED LUMINARES:- 2' X2' (FULL GLOW TYPE) LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRC010R0 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:- DIMPORTMENT OF CORD AND ALL OF CORD AN		Description of light /fan fixture			
LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO10RO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit) CG:- LCTAR3-40-CDL (b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-		equipments in surface/recess mounted as directed etc down rods of size upto 300 mm where ever required with ball sockets, anchor fastner etc complete as per site conditions. All fittings should be hang with suitable size of GI wire to four corner of fittings to the RCC rooftop with suitable size of anchor fastner/heavy gauge screw. The necessary arrangement is made by the contractor to install fittings in false ceiling especially 2'X2' and 4'X1' etc. as per			
(b) LED DOWNLIGHTER: 15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-	(a)	LED light fittings (600 X600mm) dimension suitable for grid/gypsum ceiling complete with its electrionic driver as required per instruction of Bank's Model No are as under:- PHILIPS:- RC380B G2 LED 35S-6500 PSU OD WH LED (FULLGLOW) WIPRO:- CRCO1ORO 38 HP57 HAVELLS:- LHECDIL7IL1W036 (Edge- Lit)	6	Nos	
15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH) CG:- LC DD-15-CDL, (c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-	(b)	LED DOWNLIGHTER:			
(c) LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-		15 Watt, recessed mounted circular down lighter, 6" dimension with complete its electronic driver are as under:- PHILIPS:- GREENLED-DN193B LED-12S-6500 PSU WIPRO:- IRIS LED LD 71-121-XXX-50-XX HAVELLS:- LHEBJNP ZPZ 1W 015(ENDURA LOW DEPTH)	141	Nos	
SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-	(c)	LED DOWNLIGHTER:SURFACE MOUNTED FOR FRONT	17	1403	
	(0)	SIDE(EXTERNAL) 15 Watt, surface mounted circular/square down lighter, 6" dimension with complete its electronic driver are as under:-	2	Nos	

(d)	LED COVE/ STRIP LIGHT WITH ITS ELECTRONIC DRIVER(BLUE COLOUR):- Supply, installation, testing and commissioning of bright LED strip light with its electronic driver complete as required.			
(e)	PHILIPS, WIPRO, HAVELLS, CG, BAJAJ Providing & fixing of "Digital Clock" /Digital Panel indicating Time, Day, Date, Temperature at outside of big size,(Ajanta - OLC-1070) as suitable over the facade as advised by the Bank with standard power back up. Make:- Ajanta, Titan	20	Mtr	
(f)	BOX TYPE LUMINAIRES: LED TUBE FITTINGS, 1200mm, 18/20 Watt PHILIPS/WIPRO/HAVELLS/CG	10	Nos Nos	
(g)	CEILING FAN: Single phase heavy duty grease filled double ball bearing, aerodynamically designed heavy gauge aluminium blades, copper wounded and impregnated silicon stamping motors etc 1200 mm sweep, brilliant white	10	NUS	
(h)	CG/USHA/ ORIENT/HAVELLS EXHAUST FAN:- Single phase, 300mm sweep, 900 rpm, metallic exhaust fan of the following single phase Exhaust fan continuously rated, capacitor start and run type, totally enclosed and ruggedly built, pre lubricated double ball bearing, copper wounded, A & E class insulation, dynamically balanced, below 40 db sound level etc, front cover with grill/gravity louver for protection purpose with 12 mm plywood complete in all respect make as under: CG/USHA/ORIENT/HAVELLS/ALMONARD/ALSTOM	1	Nos Nos	
(i)	WALL FAN:- Oscillating wall fan with regulator i/c coonections etc complete as required as per approved make, Sweep 400 mm , RPM 1300 make are as under: CG/USHA/ ORIENT/HAVELLS	12	Nos	
	TOTAL:- (B) LIGHT AND FAN FIXTURE			
(C)	AIR CONDITIONING WORK			
	Supply, installation, testing and commissioning of following AIR CONDIRIONERS as under. The Rate shall be inclusive of all taxes excluding GST. GST will be paid additionally by the Bank as applicable subject to GST Number. and system has complete one year warranty & If any additinal warranty provided by company/vendor in any specific part like compressor etc that is acceptable, please mentioned it.			
(i)	Supply, installation, testing and commissioning of Higher Efficient models of SPLIT AC, FIVE STAR RATING OF BEE AIR CONDITIONERS 1.5 Ton Machines confirming to latest Indian Standards and suitable for operation on 230 Volts + 10 %, single Phase, 50 Hz AC supply with rotary compressor, Refrigerant and capable to perform cooling, dehumidifying, Air Circulating, auto mode, auto swing, anti bacteria filtering, ventilation and with remote control with Cool/Fan/Dry/Auto mode, sleep mode & on/off timer with suitable thermostat. The rate should include installation charges after making appropriate changes in existing false ceiling. Heavy ready made/fabricated M S Stand to house the out door unit as per site conditions including carpentry work, minor civil work and material including copper piping of hard & prime quality of min. 22 G upto 5 metres with class "o" Nitrile insulation 12mm, cabling from indoor to outdoor unit, heavy gauge PVC drain piping with insulation as per site requirement. The copper piping, drains piping and electrical cabling should be fixed with clamps and no loose piping/cabling is allowed. The out door unit should be anti-rust powder coated. Indoor unit should have LED display. The rates inclusive of all repairs of civil and carpentry work The cost includes original fill and additional top up of refrigerant gas as per site condition. Make of ACs:- Daikin/Hitachi/Voltas/Bluestar/Carrier only		Nos	

(ii)	Supply and installation of soft & prime quality of min. 22 G Copper pipe for "Split AC only" with class "o" Nitrile insulation of minimum 12mm for split air conditioner including interconnection power/ communication cable between indoor and outdoor unit as per site requirement. (If required additionally, payment will made as per actual installtion. Make of Insulation:-Superlon/Aflex/Armacell/Kflex Make of cable:-Finolex/RR/Havells	40	Mtr	
(iii)	Drain Pipe (If Required additional) Applicale to both ACs(Cassette & Split AC). Supply and laying of heavy gauge PVC drain piping of 40mm with insulation as per site requirement with its all accessories like bend, solution etc as per site condition. (If required additionally, payment will made as per actual installtion.) Make:- Kasta/supreme	40	Mtr	
(iv)	Providing & fixing of 4 KVA Voltage stabilizer with time delay option including all accessories with installation at site (For 1Tr /1.5Tr Split AC & 1.5 Tr Cassette AC) Make:-Microtek, V-Gards	4	Nos	
(v)	Electronic Timer for auto swith on/off to AC of server/ATM/E-lobby for 4Hr/8Hr. Make:- Legrand, L&T, and other Eq. ISI make	1	Nos	
(vi)	Deinstallation and Refixing of Existing split AC after necessary cleaning with gas toping as required in the new location as per site condition inclusive all necessary civil mechinory, ply & electrical work.	2	Nos	
(C)	TOTAL:-(C)		1103	
(-)	SUMMARY			
	TOTAL:- (A) ELECTRICAL WORK			
	TOTAL:- (B) LIGHT AND FAN FIXTURE			
	TOTAL:- (C) AIR CONDITIONING WORK			
	GRAND TOTAL{ (A) + (B) + (C)} in Figure			
	GRAND TOTAL{ (A) + (B) + (C)} in Words			

GST will be paid additionally by the Bank as applicable subject to GST Number.

SEAL AND SIGNATURE OF CONTRACTOR