

BILL OF QUANTITIES

NAME OF WORK: ELECTRICAL INSTALLATION WORK FOR RENOVATION OF SILCHAR BAZAR BRANCH

SI.No.	Description	UOM	Qty.	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
1	Main Panel :- Supplying, Installing, testing and commissioning of				
	fabricated floor mounted cubicle type distribution Panel Board				
	suitable for 415 V comprising of suitable copper bus bars, 250A 4P				
	MCCB with overvoltage protection as incoming and 1 Nos. of 125A				
	4P MCCB, 2 Nos. of 100A 4P MCCB and 1 No. of 63A 4P MCCB at				
	outgoing in compartmentalized chamber fully isolated with 2 mm				
	thick steel sheet and 3 mm steel channel painted with 2 coats of red				
	oxide primer paint followed by finishing paint with interconnection				
	etc. with proper space for bus bar chamber and cable chamber as				
	required.(MCCB Make - Legrands/ Havells/L&T/SIEMENS or				
		Set	1		
	equivalent)	361			
2	Sub-main line:-				
	Wiring in MS conduit of IS specification of Proper size with core PVC				
	insulated stranded copper wire 11KV grade				
	(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEl or equivalent) and				
	with supply ,installation, commissioning of all the materials required				
	including proper termination, connection in complete as required				
	from main DB to various DBs:-				
	with 3nos 4sq.mm (1ECC)	RM	120		
	with 3nos 6sq.mm (1ECC)	RM	480		
iii)	with 5 nos 6sq.mm (1ECC)	RM	20		
3	Supply ,installation ,testing and commissioning of distribution board				
	manufactures made sheet steel enclosure With the following MCBs				
	(DB, MCB and MCCB Make - Legrands/ Havells/L&T/SIEMENS or				
	equivalent) and connecting the same to the system.				
i)	Computer/Raw power DB, SPN double door with 40A (30mA)DP				
,	RCCB as incomer & 3nos 10A SP MCB as outgoing.	No.s	5		
ii)	DB with 63A TPN MCB.	No.s	1		
iii)	DB with 63A DP MCB.	No.s	2		
	DB with 40A DP MCB.	No.s	2		
iv)	DB with 16A DP MCB.	No.s	2		
v)	DB with 25 A DP RCCB, 30mA for AC	No.s	11		
vi)	VTPN Double Door Distribution Board with 100 A 4 Pole MCCB (36kA)				
	as incomer and 6 Nos. 32A SP MCB's at outgoing	Set	2		
vii)	VTPN Double Door Distribution Board with 125A 4 Pole MCCB (36kA)				
	as incomer and 1 No. of 63A TPN MCB, 4 nos. of 40 A SP MCB, 5 nos.				
	of 32 A SP MCB, 2 nos of 16A SP MCB at outgoing	Set	1		

viii) Light D8 SPN double door with 32A (30mA)DP MCB as incomer & 3nos 10A SP MCB as outgoing. 4 Supplying, installing and commissioning of PVC Armoured cable complete with proper cable glands and two nos. of 85WG GI wire (Havells/Richo/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel, Power Distribution Board to various D8s. ii) With 3.5 core x 35 sq. mm cable 5 Supply, installing and commissioning of earth station including diaging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly finned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm/2mt,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth confinuity wire of 2x10sq.mm copper stranded PVC green color in heavy duly MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1kV grade(Finolex/Havells/Polycab/ RR Kabel/ Richo/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB/Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of pointing Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated).duly fitted with screw to the steel enclosure (cadmium plated).duly fitted with screw to the steel enclosure (cadmium plated).duly fitted with screw to the steel enclosure (cadmium plate) and be	SI.No.	Description	UOM	Qty.	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
complete with proper cable glands and two nos. of 8SWG GI wire (Havell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel, Power Distribution Board to various D8s. i) With 3.5 core x 35 sq. mm cable RM 60 Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly tinned through out the surface of the plate, placed at least 1.5Mt.below the ground level with 2nos 10sq.mm PVC insulated standed copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm.2mtr.long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty M5 conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in M5 conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1kV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB/Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the M5 conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of pointing Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48[maximum three points in single circuit) ii) With 3nos 6A socket with individual switch. No.s. 30 iii) With 1nos 16A socket	∨iii)			4		
complete with proper cable glands and two nos. of 8SWG GI wire (Havaell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main PoneJ. Power Distribution Board to various DBs. i) With 3.5 core x 35 sq. mm cable RM 60 5 Supply, installing and commissioning of earth station including diaging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly tinned through out the surface of the plate, placed at least 1.5Mt.below the ground level with 2nos 10sq.mm PVC insulated standed copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr.long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duly MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1kV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB/Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the some with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate hype switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be seeled to make the box vermin proof.848(maximum three points in single circuit) ii) With 1nos 16A socket with individual switch. No	4	Supplying, installing and commissioning of PVC Armoured cable				
(Hovell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel, Power Distribution Board to various DBs. With 3.5 core x 352, mm coble RM 145						
materials required including proper connection in complete as required from main Panel, Power Distribution Board to various DBs. With 3.5 core x 35 sq. mm cable RM 145						
required from main Panel, Power Distribution Board to various DBs. With 3.5 core x 35 sq. mm cable RM 145						
ii) With 3.5 core x 35 sq. mm cable RM 60 5 Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly finned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm.2mt.long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single care PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Rlcha/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be cavered with blank plate and be sealed to make the box vermin proof.848(maximum three points in single clicuit) i) With 2nos 16A socket with individual switch. No.s 20 iii) With 2nos 16A socket with individual switch. No.s 12						
ii) With 3.5 core x 120 sq. mm cable 5 Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly tinned through out the surface of the plate, placed at least 1.5Mtr.bellow the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm./2mtr.long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CD8/PD8(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing. testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated).duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.848/maximum three points in single circuit) 1) With 2nos 16A socket with insigle 16A switch. No.s. 20 1) With 2nos 16A socket with individual switch. No.s. 12	i)		RM	145		
digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly finned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 105q,mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq,mm copper stranded PVC green color in heavy duly MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq,mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB/Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be seeled to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 20 iii) With 3nos 6A socket with individual switch. No.s 12	- 7	·				
digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly finned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 105q,mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq,mm copper stranded PVC green color in heavy duly MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq,mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB/Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be seeled to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 20 iii) With 3nos 6A socket with individual switch. No.s 12						
x300mm size copper plate duly finned through out the surface of the plate, placed at least 1.5Mtr.below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr.long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.848(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 20 iii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp, Make : Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.	5					
plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq,mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. Set 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq,mm single core PVC insulated stranded copper wire 1.1kV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with individual switch. No.s 20 With 1nos 16A socket with individual switch. No.s 12						
10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr.long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1kV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coods of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 20 With 1nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw) . The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (codmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.848(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s. 30 ii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 1nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch.		•				
reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. Set 5 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1kV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.848(maximum three points in single circuit) i) With 3nos 6A socket with individual switch. No.s. 30 ii) With 2nos 16A socket with individual switch. No.s. 20 iii) With 2nos 16A socket with individual switch. No.s. 12						
laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s. 30 ii) With 1nos 16A socket with individual switch. iii) With 1nos 16A socket with individual switch. No.s. 12						
green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
starting point of the line earth connector. 6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
6 Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. ii) With 2nos 16A socket with individual switch. No.s. 30 iii) With 1nos 16A socket with individual switch. No.s. 12 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.				5		
of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		starting point of the line earth connector.	001	Ŭ		
copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEl or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s. 30 ii) With 2nos 16A socket with individual switch. No.s. 12 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.	6	Computer/Raw Power point wiring in MS conduit of IS specification				
Richa/KEI or equivalent) and with all material supply installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		of proper size with 3nos 2.5sq.mm single core PVC insulated stranded				
commissioning complete from CDB/PDB(Raw) .The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing .All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/				
carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		Richa/KEI or equivalent) and with all material supply installation and				
carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		commissioning complete from CDB/PDB(Raw) .The wiring shall be				
surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing .All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing .All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make: Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		-				
testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
(Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated), duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
enclosure (cadmium plated), duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof. B48 (maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
conduit and fixed to the wall partition furniture with all interconnection and proper earthing. All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
interconnection and proper earthing .All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. No.s 30 ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		·				
proof.B48(maximum three points in single circuit) i) With 3nos 6A socket with single 16A switch. ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		interconnection and proper earthing .All the opening shall be				
i) With 3nos 6A socket with single 16A switch. No.s 30 With 2nos 16A socket with individual switch. No.s 20 With 1nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.		covered with blank plate and be sealed to make the box vermin				
ii) With 2nos 16A socket with individual switch. No.s 20 iii) With 1nos 16A socket with individual switch. No.s 12 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.				2.5		
iii) With 1nos 16A socket with individual switch. 7 Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
7 Supply, installation testing and commissioning of recessed mounted Nos circular LED downlighter with 15W LED lamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.						
circular LED downlighter with 15W LED lamp. Make :- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent.	,	The state of the s				
		circular LED downlighter with 15W LED lamp.	Nos			
				56		

SI.No.	Description	UOM	Qty.	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
8	Supply, installation testing and commissioning of recessed type LED luminaire with complete PMMA Difuser with 35W LED lamp (size 2"X 2"). Make :- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent		35		
9	Supply installation testing and commissioning of LED batten Single Tube light fittings with 17W with glare free light distribution wall mounted at ceiling/false ceiling level/. Make :-Bajaj/Havels/Phillips/Wipro/Crompton or equivalent		24		
10	Supply and installation of Wall Mounted fan 400 mm Metallic body and metallic Blade ,1400 rpm of crompton/bajaj/usha/orient/Havells make or equivalent		24		
11	Supply and installation of 5 Star rated Ceiling fan 1200 mm crompton/bajaj/usha/havell's make	No.s	4		
12	Supply and installation of Heavy Duty metallic body & Blades Exhaust Fan 300 mm crompton/bajaj/usha/havell's make	No.s	6		
13	Supplying, installation, testing & commissioning of Security light with 25W LED lamps with pressure die cast housing with epoxy coated dark graphite grey colour finish and prismatic polycarbonates cover with individual LED lenses, including necessary GI bracket with clamp. Make:- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent		4		
i) ii)	Wiring for light/fan/exhaust fan points using 3 X 1.5 Sq MM 1.1 kV grade PVC insulated stranded copper conductor wire (Finolex/Havell's/Richa/RR kebel/KEI or equivalent) for phase, neutral and earth in 25 mm dia heavy duty MS conduit along with associated accessories like MS junction boxes, bends, saddles, screws et. concealed in wall, floor, under flooring, below false ceiling or on surface as well as suspended from ceiling with 25mm X 3 mm MS flat suspenders duly painted above false ceiling from individual light/Fan/Exhaust Fan point outlet. etc. to individual modular type switch boards, 10 Amp modular plate type switches etc. (MK/Legrands/Havel's or equivalent), as required complete including circuit wiring with 3 X 2.5 sqmm. 1.1 kV grade PVC insulated stranded copper conductor wire and as per site requirement and as instructed by SBIIMS Engineer. one light/fan controlled by one switch 6A socket & switch at same board		155		
iii)	Fan Point with electronic modular type regulator. GST on work contract will be extra as applicable.	4	Grand Total in Rs		