## RENOVATION OF AKULATO BRANCH BOQ for Electrical Installation Works

CL N	DESCRIPTION		1	D == 1 = (D = )	
SL NG	DESCRIPTION	UOM	<u>Q1Y</u>	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
1	a. Main Panel :- Supplying, Installing, testing and commissioning of factory fabricated 2MM thick CRCA, floor mounted cubicle type districution Panel Board with 150 MM X 75 MM X 6MM ISMC base channel, suitalbe for 415 V TPN comprising of 300A suitable copper bus bars with color codded heat shrink insulation with the followings: 160 A, 4P MCCB, 50 kA with overvoltage protection as incommer, R-Y-B LED indicating lamps, Digital multifunction meter of minimum size 150 MM X 150 MM to measure Voltage, Current, PF etc with all excessories Outgoing:100 A 4P MCCB, 35kA for AC -1 Nos, 63 Amp TPN MCCB, 35kA for AC - 1 No, 63 Amp TPN MCCB, 35 kA -1 Nos. for External equipment and raw Power. All MCCBs are strictly as specified above only. All outgoing must be in compartmentalized chamber fully isolated with 2 mm thick CRCA and 3 mm steel channel painted with 2 coats of red oxide primer paint followed by finishing paint with interconnection etc. as required.	Set	1		
2	Sub-main line:- Wiring in MS conduit of IS specification of Proper size with core PVC insulated stranded copper wire 11KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with supply ,installation, commissioning of all the materials required including proper termination,connection in complete as required from main DB to various DBs:-				
i)	with 3nos 4sq.mm (1ECC)	RM	60		
ii)	with 3nos 6sq.mm (1ECC)	RM	50		
3 i)	Supply installation ,testing and commissioning of distribution board manufactures made sheet steel enclosure With the following MCBs (DB,MCB and MCCB Make- Legrands/ Havells/ L&T/ SIEMENS or equivalent) and connecting the same to the system. Computer/Raw power DB, SPN double door with 40A (30mA)DP RCCB as incomer & 5 nos 10A SP MCB as outgoing.	No.s	2		
::)	DB with 32A DP MCB.	No.s			
ii) iii)	DB with 16A DP MCB.(Security and signboard)	No.s	4		
iv)	DB with 32A DP RCCB.	No.s	3		
$\vee$	DB with 32A MCB Changeover	Nos.	1		
viii)	VTPN Double Door Distribution Board with 63A 4 Pole MCCB (36kA) as incomer and 5 nos. of 40 A SP MCB, 2 Nos. of 32A MCB and 2 nos of 16A SP MCB at out going	Set	1		
	TPN DB with 63 4P MCB as incoming and 4 nos. of 32A SP MCB, 2 Nos 10A SP MCB as outgoing.( for AC and RAW power)	Set	1		
	Light DB SPN double door with 40A (30mA)DP RCCB as incomer & 5 nos 10A SP MCB as outgoing.	No.s	1		
4	Supplying, installing and commissioning of PVC Armored cable complete with proper cable glands and two nos. of 8SWG GI wire (Havell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel,Power				
	Distribution Board to various DBs .				
i)	Distribution Board to various DBs . With 3.5 core x 35 sq. mm cable With 3.5 core x 25 sq. mm cable	RM	30		

SI M	DESCRIPTION		1	Parto (Pal)	Amount (Dr.)
JL IN	DESCRIPTION	NON		Rate (Rs.) (Exclusive of GST on work	Amount (Rs.) (Exclusive of GST on work
			<u>QTY</u>		
				contract)	contract)
5	Supply, installing and commissioning of earth station including digging and	Nos.			connacty
	refilling back the pit with black soil and with 3.15mm x300mm size copper				
	plate duly tinned through out the surface of the plate, placed at least				
	1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded				
	copper conductor in 20mm GI pipe, fixed to the plate and providing		4		
	40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe	1	4		
	with supplying and laying earth continuity wire of 2x10sq.mm copper				
	stranded PVC green color in heavy duty MS conduit on the wall from earth				
	plate to starting point of the line earth connector with proper earth pit.	RM			
	i) Supplying and fixing 25x3 mm copper strip, insulated by heat pressurized heavy gauge PVC sleeve, duly jointed by full lap brazing	K/VI			
	and drawn underground in 40 mm class B GI pipe from the inspection		10		
	pit to the inside of the branch premises.				
	ii)Supplying and fixing 2X8 SWG dia copper earth wire in PVC conduit	RM			
	on surface or in recess for loop earthing from panel to DB		50		
5	Computer/Raw Power point wiring in MS conduit of IS specification of				
	proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper				
	wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEl or				
	equivalent) and with all material supply installation and commissioning				
	complete from /PDB(Raw). The wiring shall be carried out on surface above				
	false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like				
	saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface				
	including supply installing, testing, commissioning of modular plate type				
	switch and socket (Legrands / MK or equivalent) for computer				
	terminal on sheet steel enclosure (cadmium plated), duly fitted with screw				
	to the steel conduit and fixed to the wall partition furniture with all				
	interconnection and proper earthing .All the opening shall be				
	covered with blank plate and be sealed to make the box vermin				
	proof.B48(maximum three points in single circuit)				
)	With 3nos 6A socket with single 16A switch.	No.s	12		
i)	With 2nos 16A socket with individual switch.	No.s	7		
; ii)	With 1nos 16A socket with individual switch.	No.s	4		
7	Supply, installation testing and commissioning of recessed mounted		1		
	circular LED downlighter with 15W LED lamp. Make :-		20		
	Bajaj/Havels/Phillips/Wipro/Crompton or equivalent. (Model: Havells		22		
	INTEGRANXTDLR15WLED857S TR or Equivalent specification)				
8	Supply, installation testing and commissioning of recessed type LED luminaire	Nos			
	with complete PMMA Difuser with 36 W LED lamp (size 2"X 2") (Model:Plano or		8		
	equivalent) . Make : Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent				
>	Supply installation testing and commissioning of LED batten Single Tube light	Nos			
	fittings with 20W (Model: Havells LUMILINEBS20WLED865SPCWH or equivalent				
	Specification) with glare free light distribution wall mounted at ceiling/false		14		
	ceiling level/. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent				
0	Supply and installation of Wall Mounted fan 400 mm full Metallic body and	No.s			
	metallic Blade, 1400 rpm crompton/ bajaj/ usha/ orient make		5		
11	Supply and installation of Ceiling fan 1200 mm crompton/ bajaj/ usha/	No.s			
	havells make		2		
12	Supply and installation of heavy duty Exhaust Fan 300 mm crompton/ bajaj/	No.s	2		
	usha/ havells make		_		

CL 11	DESCRIPTION				
SL NO	DESCRIPTION	NON		Rate (Rs.)	Amount (Rs.)
			QTY	(Exclusive of	(Exclusive of
			<u></u>	GST on work	GST on work
				contract)	contract)
13	Supplying, installation,testing & commissioning of Security ligh with 25W LED lamps with pressure die cast housing with epoxy coated dark graphite grey colour finish and prismatic polycarbonates cover with individual LED lenses, including necessary GI bracket with clamp. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos.	4		
16	Wiring for light/fan/exhaust fan points using 3 X 1.5 1.1 kV grade PVC insulated stranded copper conductor wire (Finolex/ Havell's/ Richa/ RR kebel/ KEI or equivalent) for phase, neutral and earth in 25 mm dia heavy duty MS conduit along with associated accessories like MS junction boxes, bends, saddles, screws et. concealed in wall, floor, under flooring, below false ceiling or on surface as well as suspended from ceiling with 25mm X 3 mm MS flat suspenders duly painted above false ceiling from individual light/Fan/Exhaust Fan point outlet. etc. to individual modular type switch boards, 10 Amp modular plate type switches etc.(MK/Legrands/Havel's or equivalent), as required complete including circuit wiring with 3 X 2.5 sqmm. 1.1 kV grade PVC insulated stranded copper conductor wire and as per site requirement and as instructed by SBII/MS Engineer.				
i)	Light/fan point (Two downlighter/ 2"X 2" rececced light fittings to be connected through one point)	No.s	45		
ii)	6A socket & switch at same board	No.s	5		
iii)	Fan Point with electronic modular type regulator.	No.s	2		
i∨)	16A, 5 pin industrail plug & Socket with 25 A MCB protected (for Safe room & Record room)	Nos.	2		
v)	Modular type with 6A SP MCB for Exhaust fan and wall fan	No.s	7		
	Total				
	oldreid an article and the state of the stat				

GST on work contract will be extra as applicable.