## OPENING OF HALWATING BRANCH, ASSAM BOQ for Electrical Installation Works

SL No	DESCRIPTION	UOM		Rate (Rs.)	Amount (Rs.)
			OTV	(Exclusive of	(Exclusive of
			<u>QTY</u>	GST on work	GST on work
1	<b>a. Main Panel</b> : Supplying, Installing, testing and commissioning of factory fabricated 2MM thick CRCA, floor mounted cubicle type districution Panel Board with 150 MM X 75 MM X 6MM ISMC base channel, suitalbe for 415 V TPN comprising of 200A suitable copper bus bars with color codded heat shrink insulation with the followings: 160 A, 4P MCCB, 35 kA with overvoltage protection as incommer, R-Y-B LED indicating lamps, Digital multifunction meter of minimum size 150 MM X 150 MM to measure Voltage, Current, PF etc with all excessories Outgoing: 63 A 4P MCCB, 35kA for AC -1 Nos 63 Amp TPN MCCB, 35kA for UPS & SPRAE - 2Nos, 40 A 4P MCCB -2 nos for External equipment and ATM. All MCCBs are strictly as specified above only. All outgoing must be in compartmentalized chamber fully isolated with 2 mm thick CRCA and 3 mm steel channel painted with 2 coats of red oxide primer paint followed by finishing paint with interconnection etc. as required.	Set	1	contract)	contract)
	b. Capacitor Panel: Supply and installation of 20 KVAR APFC panel, floor/wall mounted front operated totally enclosed vermin proof, indoor non-drawout-cubicle type power panel fabricated out of 16 SWG thick CRCA sheet having gasketed hinged cover on each cubicle fully powder coated with suitable bus bar for connecting the contactors, MCB's, Capacitors, etc with the following acessories A set of R-Y-B LED indicating lamp at incomer 40 A, TPN MCB, as incomer - 1No 1 No. 32A 3P contactor for 10 KVAR, 1 Nos. 25A 3P contactor for 5 KVAR, 2 Nos, 16A, 3P contactor for 2 KVAR and 1 No, 10 A, 3P contactor for 1 KVAR 1 No. 10 KVAR, 1 Nos. 5 KVAR, 2 Nos. 2 KVAR and 1 No. 1 KVAR. 1 no. 6-step APFC relay of minimum size 150 MM X 150 MM suitable for above arrangement ON/OFF push button for each capacitor ON/OFF LED type indication lamp for each capacitor		1		
2	Sub-main line:- Wiring in MS conduit of IS specification of Proper size with core PVC insulated stranded copper wire 11KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with supply ,installation, commissioning of all the materials required including proper termination,connection in complete as required from main DB to various DBs:-				
i)	with 2nos 4sq.mm and 1 no. 2.5 sqmm(1ECC)	RM	160		
ii)	with 2nos 6sq.mm and 1 no. 4 sqmm (1ECC)	RM	90		
3	Supply ,installation ,testing and commissioning of distribution board manufactures made sheet steel enclosure With the following MCBs (DB,MCB and MCCB Make- Legrands/ Havells/ L&T/ SIEMENS or equivalent) and connecting the same to the system.				

SL No	DESCRIPTION	UOM		Rate (Rs.)	Amount (Rs.)
			<u>QTY</u>	(Exclusive of GST on work contract)	(Exclusive of GST on work contract)
i)	Computer/Raw power DB, SPN double door with 40A (30mA)DP	No.s		connacty	comiden
',	RCCB as incomer & 6 nos 10A SP MCB as outgoing.		2		
ii)	DB with 32A DP MCB.	No.s	4		
iii)	DB with 16A DP MCB.(Security and fire)	No.s	4		
iv)	DB with 32A DP RCCB.	No.s	8		
V)	DB with 32A MCB Changeover	Nos.	1		
∨ii)	Supply & installation of double door 4 way ETPN MCB DB with following accessories a)1 No.40 amp. TPN MCB as incomer, b) 4 Nos. 25 Amps SP MCB and 2 nos. 16A SP MCB in outgoing (& ATM	Nos.	1		
viii)	VTPN Double Door Distribution Board with 63A 4 Pole MCCB (36kA) as incomer and 6 nos. of 40 A SP MCB, 2 Nos. of 32A MCB and 2 nos of 16A SP MCB at out going	Set	1		
∨iii)	VTPN Double Door Distribution Board with 63A 4 Pole MCCB (36kA) as incomer and 8 nos. of 32 A SP MCB,	Set	1		
ix)	Light DB SPN double door with 40A (30mA)DP RCCB as incomer $\&$ 6 nos 10A SP MCB as outgoing.	No.s	2		
4	Supplying, installing and commissioning of PVC Armored cable complete with proper cable glands and two nos. of 8SWG GI wire (Havell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel, Power Distribution Board to various DBs.				
i)	With 3.5 core x 25 sq. mm cable	RM	40		
i)	With 3.5 core x 35 sq. mm cable	RM	40		
ii)	With 3.5 core x 50 sq. mm cable	RM	40		
5	Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly tinned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector with proper earth pit.  i) Supplying and fixing 25x3 mm copper strip, insulated by		5		
	heat pressurized heavy gauge PVC sleeve, duly jointed by full lap brazing and drawn underground in 40 mm class B GI pipe from the inspection pit to the inside of the branch premises.	ΚM	30		
	ii)Supplying and fixing 2X8 SWG dia copper earth wire in PVC conduit on surface or in recess for loop earthing from panel to DB	RM	80		

SI NIC	DESCRIPTION	NON		Pato (Pa )	Amount (Da )
3L NO	DESCRIPTION	UOM		Rate (Rs.) (Exclusive of	Amount (Rs.) (Exclusive of
			<u>QTY</u>	GST on work	GST on work
				contract)	contract)
6	Computer/Raw Power point wiring in MS conduit of IS			Connact)	Corniacij
°					
	specification of proper size with 3nos 2.5sq.mm single core				
	PVC insulated stranded copper wire 1.1KV				
	grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or				
	equivalent) and with all material supply installation and				
	commissioning complete from /PDB(Raw) .The wiring shall be				
	carried out on surface above false ceiling by chiseling the				
	existing surface and plastering the same with cement etc.				
	after fixing the MS conduit with all accessories like saddles				
	screws, bends T-joint etc. 2 coats of painting Matching to the				
	surface including supply installing, testing, commissioning of				
	modular plate type switch and socket (Legrands / MK or				
	equivalent) for computer terminal on sheet steel enclosure				
	(cadmium plated), duly fitted with screw to the steel conduit				
	and fixed to the wall partition furniture with all interconnection				
	and proper earthing .All the opening shall be covered				
	with blank plate and be sealed to make the box vermin				
	proof.B48(maximum three points in single circuit)				
	MACHE On an AA and a land willing the size of a 1/A and the land	NI	1.5		
1)	With 3nos 6A socket with single 16A switch.	No.s	15		
ii)	With 2nos 16A socket with individual switch.	No.s	10		
iii) 7	With 1nos 16A socket with individual switch.  Supply & Fixing of 15Watt commercial down lights of system	No.s	4		
′	efficacy >100lm/W. The light should be recessed mounted slim				
	circular type LED panel with <b>die-cast aluminium housing</b> and				
	smooth powder coated finish with anti-glare UV stabilized diffuser		40		
	and separate energy efficient electronic driver having inbuilt		40		
	surge protection upto 2.5kV. (Make - as in tender make list)				
	sorge profession opto 2.3kv. (Make as in terradi make iisi)				
8	Supply, installation testing and commissioning of surface	Nos			
	mounted circular LED downlighter with 15W LED lamp. Make:				
	Bajaj/Havels/Phillips/Wipro /Crompton or equivalent. (Model:		5		
	Havells GLOWDLS15WLED830S or Equivalent Specification)		-		
9	Supply and fixing of 2'x2' LED commercial Luminaire of 36 Watt				
	with system efficacy of 110lm/W. The light should be recessed				
	mounted type and low depth with CRCA poweder coated				
	housing, high transmittance diffuser for sysmmetric light		24		
	distribution with non-integral enegy efficient isolated electronic				
	driver and inbuilt surge protection upto 3kV. (Make - as in tender				
	make list)				
10	Supply and fixing of LED commercial batten Single Tube light				
	fittings with 20W with glare free light distribution wall mounted at		16		
	ceiling/false ceiling level/. (Make - as in tender make list)		10		
		<u> </u>			
11	Supply and installation of Wall Mounted fan 400/450 mm <b>Metallic</b>	No.s	6		
	body and metallic Blade ,1400 rpm Havels FHWV3TFSLB18 or		8		
	equivalent (Make - as in tender make list)	<u> </u>			
12	Supply and installation of Heavy Duty metallic body & Blades	No.s			
	Exhaust Fan 300 mm (Make - as in tender make list) (in toilet and		7		
	UPS room) including aking suitable size hole in the wall.				

SL No	DESCRIPTION	UOM	<u>QTY</u>	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
13	Supplying, installation, testing & commissioning of Security ligh with 25W LED lamps with pressure die cast housing with epoxy coated dark graphite grey colour finish and prismatic polycarbonates cover with individual LED lenses, including necessary GI bracket with clamp. Make: Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos.	6		
14	Strip surface mounted alongwith required LED Driver as back lighting. Havells or equivalent make.	No.s	10		
15	Wiring for light/fan/exhaust fan points using 3 X 1.5 1.1 kV grade PVC insulated stranded copper conductor wire (Finolex/ Havell's/ Richa/ RR kebel/ KEI or equivalent) for phase, neutral and earth in 25 mm dia heavy duty MS conduit along with associated accessories like MS junction boxes, bends, saddles, screws et. concealed in wall, floor, under flooring, below false ceiling or on surface as well as suspended from ceiling with 25mm X 3 mm MS flat suspenders duly painted above false ceiling from individual light/Fan/Exhaust Fan point outlet. etc. to individual modular type switch boards, 10 Amp modular plate type switches etc.(MK/Legrands/Havel's or equivalent), as required complete including circuit wiring with 3 X 2.5 sqmm. 1.1 kV grade PVC insulated stranded copper conductor wire and as per site requirement and as instructed by SBIIMS Engineer.				
i)	Light/fan point ONE downlighter/ 2"X 2" rececced light fittings to be connected through one point)	No.s	40		
ii)	Light/fan point (Two downlighter/ 2"X 2" rececced light fittings to be connected through one point)	No.s	30		
iii)	Light/fan point (four downlighter/ two 2"X 2" rececced light fittings to be connected through one point)		12		
iv)	6A socket & switch at same board	No.s	8		
<b>v</b> )	16A, 5 pin industrail plug & Socket with 25 A MCB protected (for Safe room & Record room)	Nos.	2		
vi)	Modular type with 6A SP MCB for Exhaust fan and wall fan	No.s	15		
	Total				

GST on work contract will be extra as applicable.