S.No.	DESCRIPTION OF WORKS	UNIT	QTY	RATE	AMOUNT
1	Wiring for light point/ fan point/ wall fan point/ exhaust fan/				
	light sockets etc. with 1.5 sq.mm. PVC insulated 1100 V				
	Grade copper conductor (FRLS) wires & 1.5 sq.mm. copper				
	earth wire in concealed/ surface using 16 SWG MS conduits,				
	accessories such as bends, tees, saddles, draw boxes, mounting				
	boxes, inner plates, cover plates, ceiling rose etc (whereever				
	required) and chromium plates brass screws/ rowel plug etc.				
	The circuit wiring starting from DB to point control box/				
	switch box using 2 X 2.5 sq.mm PVC insulated 1100 V grade				
	multi- stranded copper conductor wire & 2.5 sq.mm. PVC				
	insulated earth wire (color code to be used). (Flexible conduit/				
	elbow not allowed). The conduit to be laid in ceiling with				
	proper clamps/ wall/ floor and flling the chase with cement				
	mortar and finishing the same in original form/ wooden				
	partition/ above false ceiling with proper clamps etc. all				
	complete.				
	(Wherever required as per standard specifications).				
	i) Each circuit shall have independent earth wire.				
	ii) Each point shall be earthed.				
	iii) Circuit wiring is to be included in point wiring rates.		1.00		
i	One light points controlled by one 6 amp. Modular switch	Nos.	4.00		
ii	Two light points controlled by one 6 amp. Modular switch	Nos.	11.00		
iii	Three light points controlled by one 6 amp. Modular switch	Nos.	2.00		
iv	Four light points controlled by one 6 amp. Modular switch	Nos.	2.00		
v	Five light points controlled by one 6 amp. Modular switch	Nos.	1.00		
vi	One call bell point with ceiling rose/ 6amp. 3 pin socket	Nos.	1.00		
V1	controlled by one 6 amp. Push Modular switch. With call bell	1105.	1.00		
vii	One wall fan/ exhaust fan point controlled by one 6 amp.	Nos.	10.00		
	Modular switch. The switch should be at switchboard level				
viii	One 5 pin socket controlled by one 6 amp. Modular switch				
	complete assembly includes plate box etc.				
a	Dependent	Nos.	6.00		
x	Same as serial no 1 but using 2*2.5 + 1*2.5 Sqmm Copper				
л	Conductor FRLS wires from DB to first 6A, 5 Pin modular				
	socket controlled by one 6A switch and looped to the nearest				
	second point with same $2*2.5 + 1*2.5$ Sqmm copper				
	conductor wires FRLS insulated 1100V grade.				
	conductor writes rikels insulated 1100 v grade.				
a	Primary	Nos.	7.00		
b	Secondary	Nos.	13.00		
xi	Same as serial no 1 but using 2*2.5 + 1*2.5 Sqmm Copper				
	Conductor FRLS wires from DB to first 16 Amp MCB two				
	Nos., for Glow sign Board.				
а	Primary Point	Nos.	2.00		
	1				

a) b) 3(a)	Same as serial no.1, but wiring for 16 Amp, 6-pin sockets by using 2*4 sq.mm. PVC insulated 1100 V grade copper conductor wire with independent 1* 4.0 sq.mm earth wire from D.B. to first point 1 st socket and 1 st to 2 nd , socket with 2*2.5 sq.mm. and 1*2.5 earth wire including providing and fixing of 16 Amp, 6 –pin socket with 16 Amp. Switch. (Modular type switch/ socket/ plate etc. complete assembly). Primary point Secondary point Same as serial no.1, but wiring for A/C socket by using 2*4 sq.mm. PVC insulated 1100 V grade copper conductor wire and earthing with 1*4.0 sq.mm. PVC insulated 1100 V grade copper conductor wire with modular type AC box(tiny trip type) with socket complete in all respects controlled by 25/32 A SP MCB to be provided near indoor unit. The point starts from DB to stabilizer to the point near the indoor unit including top.	Nos. Nos. Nos.	6.00 6.00 3.00		
3(b)	Same as serial no.1, but wiring for A/C socket by using 2*4 sq.mm. PVC insulated 1100 V grade copper conductor wire and earthing with 1*4.0 sq.mm. PVC insulated 1100 V grade copper conductor wire of weather proof type 2 way SPN DB complete in all respects controlled by with 32 Amp (10 KA) MCB to be provided near outdoor unit. The point starts from DB to the point near the outdoor unit. Item to also include termination lid between MCB and outdoor unit.	Nos.	2.00		
3(c)	Same as serial no.1, but wiring for A/C socket by using 4*6 sq.mm. PVC insulated 1100 V grade copper conductor wire and earthing with 1*6.0 sq.mm. PVC insulated 1100 V grade copper conductor wire and weather proof type 4 way SPN DB complete in all respects controlled by with 40 Amp TPN (10 KA) MCB to be provided near outdoor unit. The point starts from DB to the point near the outdoor unit (includes wires for terminal connection of outdoor unit from TPN) including wiring to the terminals of the outdoor unit from weather proof box. Item to also include termination lid between MCB and outdoor unit.	Nos.	1.00		
4	COMPUTER POINTS				
а	Wiring with $2x2.5$ sq.mm. + $1x2.5$ sq.mm. PVC insulated 1100 V grade multi stranded copper conductor wires in 2 mm thick PVC conduit from UPS DB to computer point. Each				
	point to have 3 nos. 6 amps. 5 pin modular type sockets, one 6 amps modular swtich with all accessories, inner/ outer plates, metal box etc. and to be fixed on wooden partitions/ by grouting on wall etc. as per requirement at site. The switch should be fixed above the top of counter with indicator and sockets under the counter.				
	point to have 3 nos. 6 amps. 5 pin modular type sockets, one 6 amps modular swtich with all accessories, inner/ outer plates, metal box etc. and to be fixed on wooden partitions/ by grouting on wall etc. as per requirement at site. The switch should be fixed above the top of counter with indicator and	Nos.	6.00		

b	Wiring with 2x2.5 sq.mm + 1x2.5 sq.mm PVC insulated 1100			
	V grade multi stranded copper conductor wires in 2 mm thick			
	PVC conduit from UPS DB to computer point. Each point to			
	have 1 nos. 16 amps 5 pin modular type sockets, 1 No's 16			
	amps modular swtich with all accessories, inner/ outer plates,			
	metal box etc and to be fixed on wooden partitions/ by			
	grouting on wall etc as per requirement at site. The switch			
	should be fixed above the top of counter and sockets under the			
	counter. or as directed by the engineer incharge.			
	D '	NT	1.00	
	Primary	Nos.	1.00 1.00	
	Secondary	Nos.	1.00	
B.	CONDUITING FOR TELEPHONE, COMPUTER &			
	CONDUITING, WIRING FOR T.V. SYSTEM.			
1.0	TELEPHONE SYSTEM			
1.1	Wiring for VOICE from Jack Panel in data rack to computer	Nos.	14.00	
	workstation with Cat-6 voice cable in PVC conduits of size			
	20/ 25 mm including providing ferrules at both ends and			
	termination at both ends including providing & fixing frame			
	for telephone socket with shutter, RJ 47 outlet, faceplate and			
	mounting box complete of modular type. This work includes			
	supply and laying of CAT-6 cable in PVC conduits throughout			
	the lenght, from the I/O hub to the point.			
1.2	Supplying, laying, effecting terminations, testing and			
	commissioning of 0.51 mm dia Cu. Conductor, twisted, colour			
	coded with polythene capor barrier, telephone cables in the			
	existing tray or in conduit including providing &fixing conduit			
	pipe or cable tray as required from building tag block to the			
	floor as required.	N T	1.00	
a)	Supplying & fixing 10 pair krone tag block with enclosure.	Nos.	1.00	
2	COMPUTER NETWORKING			
2.1	Wiring for computer networking from Jack Panel in data rack	Nos.	16.00	
	to computer workstation with Cat-6 computer cable in PVC			
	conduits of size 20/ 25 mm including providing ferrules at			
	both ends and termination at both ends including providing &			
	fixing frame for Cat-6 with shutter, RJ 45 outlet, faceplate and			
	mounting box complete of modular type, This work includes			
	supply and laying of CAT-6 cable in PVC conduits throughout			
	the lenght, from the I/O hub to the point.			
	-			
2.2	Supplying and fixing 9 U (Rack with glass door, opening in	Nos.	1.00	
	the front power panel 1 (horizontal), cable manager 1 lock &			
	key).			
2.3	Supply, Installation, Testing & Commissioning of 24 port Jack	Nos.	2.00	
	Panel.			
2.4	Supplying and fixing Patch Cord-2 Meter- (DBPS Mounting	Nos.	16.00	
2.5	Cord)	N	20.00	
2.5	Supplying and fixing Patch Cord-1 Meter-	Nos.	30.00	
C.	CABLES, MAINS & SUBMAINS			
<u> </u>	Supplying all materials and laying/ pulling 1100 volts grade			
	PVC insulated copper conductor wires (FRLS) in MS conduit			
	with all fixing accessories after cutting the floor, wall and the			
	like etc. and replastering the floor level to original. Conduit			
	must be 30 mm below the floor finish level.			

i	2 X 6 sq.mm. + 1 X 6 sq.mm.	RM	30.00	
iii	Supplying, laying, testing & commissioning of 4 C X 16 sq.mm. at 1100 volts grade PVC insulated aluminium conductor armoured cable with 10 gauge earth copper wire including cables end termination using appropriate Lugs, Glands, termination acessories, Clamps etc. as required as per specification (, LIGHT PLUG DB, UPS Room & Power DB).	RM	35.00	
iv	Supplying, laying, testing & commissioning of 4 C X 25 sq.mm. at 1100 volts grade PVC insulated aluminium conductor armoured cable with 10 gauge earth copper wire including cables end termination using appropriate Lugs, Glands, termination acessories, Clamps etc. as required as per specification (AC DB).	RM	10.00	
vi	Supplying, laying, testing & commissioning of 4 C X 50 sq.mm. at 1100 volts grade PVC insulated aluminum conductor armoured cable including cables end termination using appropriate Lugs, Glands, termination acessories, Clamps etc. as required as per specification (for Main Connection)	RM	40.00	
D.	DISTRIBUTION BOARD			
	Supplying, installing, testing & commissiong of surface/ recessed mountings, Double door 415 volts TPN MCB distribution board of steel steel, 1.6mm thick dust phosphatized and painted, inclusive of 100 amps, tinned copper busbars, earthbar, common neutral link, din bar for mounting of MCB's detachable gland/ knock out plate & with built in loose wire boxl, and superior make terminal connectors for all incoming and outgoing circuits duly prewired with adequate size of PVC insulated copper wires between the bus bars and the MCB's as well as the incomer and upto the terminal connectors/ neutral link and ready for installation of following ways as required.			
	Use 'B' curve MCB's for lighting & small power circuits, 'C' curve for motor duty i.e. for pumps, AC motors, window and split AC's etc. & 'D' curve for UPS DB's i.e. for computers/ PC's circuit. Main incomer & outgoing circuit MCB's shall be selected accordingly i.e. type B,C & D. Contractor to select the MCB's accordingly as per the nature of the circuit/ load.			
	Each DB shall have separate neutral links of rating not less than 100A for each phase. The main incoming neutral link shall be in addition to three outgoing neutral links and shall be of 125 A.			
	UPS DB's shall have a dedicated Earthing link fixed on insulated supports, which will be in addition to body earth link.			
	All internal inter connecting wiring with in the DB's shall be PVC insulated flexible copper conductor wires of adequate capacity as per the current rating. Inside each DB, a DB chart is to be fixed.			
а	6-way TPN DB (LIGHT DB & 6 A raw point)	No.	1.00	
	Incomer:- 1 No. 40 Amp TPN (10 KA) MCB with 40 A DP RCCB (100 MA) each phase			

	Outgoing:-			
	12 Nos.10/20 Amp (10 KA) SP MCB			
b	4-way TPN DB (POWER DB)	No.	1.00	
0	Incomer:-	110.	1.00	
	1 No. 40 Amp TPN (10 KA) MCB with 40 A DP RCCB (100			
	MA) each phase			
	Outgoing:-			
	6 Nos.10/20 Amp (10 KA) SP MCB			
	0 Nos.10/20 Amp (10 KA) SP MCB			
	9 CDN DD (UDC INDUT)	N.	1.00	
с	8-way SPN DB (UPS INPUT)	No.	1.00	
	Incomer:-			
	1 No. 63 Amp TPN			
	Outgoing:-		├	
	2 Nos.40 Amp DP MCB			
d	4-way V-TPN DB (AC)	No.	1.00	
	Incomer:-			
	1 No. 63 Amp TPN 4 Pole (16KA) MCCB			
	Outgoing:-			
	2 Nos. 32 Amp (10 KA) TP MCB			
	6 Nos. 32 Amp (10 KA) SP MCB			
f	2-way SPN DB with 40 A DP MCB (For UPS Input / output)	No.	1.00	
g	12-way SPN DB (For UPS OUTPUT)	No.	1.00	
	Incomer:-			
	1 No. 40 Amp DP (10 KA) MCB with 40 A DP RCCB (100		1 1	
	MA)			
	Outgoing:-			
	8 Nos.6/10/16 Amp (10 KA) SP MCB			
			1 1	
Е	(LIGHT FITTINGS & ACCESSORIES)			
-	Supplying, installation with hanging support, testing and			
	commissioning of following light fixtures with electronic			
	Ballaste Tubes Jamps all fixing materials including			
	Ballasts, Tubes, lamps, all fixing materials including			
	connecting wires etc. all complete as per the directions of			
	connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered			
	connecting wires etc. all complete as per the directions of			
:	connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty).	Nac	25.00	
i	connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As	Nos.	25.00	
i	connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty).	Nos.	25.00	
	connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect.			
i	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED 	Nos.	25.00	
	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender 			
ii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. 	Nos.	6.00	
	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T- 			
ii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T- 5 fitting make As specified in tender document or approved by 	Nos.	6.00	
ii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T- 5 fitting make As specified in tender document or approved by SBI/ Architect. 	Nos. Nos.	6.00	
ii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and 	Nos.	6.00	
ii iii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T- 5 fitting make As specified in tender document or approved by SBI/ Architect. 	Nos. Nos.	6.00	
ii iii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and 	Nos. Nos.	6.00	
ii iii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 	Nos. Nos.	6.00	
ii iii	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by 	Nos. Nos.	6.00	
ii iii iv	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by SBI/ Architect. Wall mounted fans 400/450 mm dia. make As specified in 	Nos. Nos. Nos.	6.00 2.00 4.00	
ii iii iv	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by SBI/ Architect. Wall mounted fans 400/450 mm dia. make As specified in tender document or approved by SBI/ Architect. (METAL 	Nos. Nos. Nos.	6.00 2.00 4.00	
ii iii iv v	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by SBI/ Architect. Wall mounted fans 400/450 mm dia. make As specified in tender document or approved by SBI/ Architect. 	Nos. Nos. Nos.	6.00 2.00 4.00 8.00	
ii iii iv	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by SBI/ Architect. Wall mounted fans 400/450 mm dia. make As specified in tender document or approved by SBI/ Architect. BODY) 	Nos. Nos. Nos.	6.00 2.00 4.00	
ii iii iv v	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by SBI/ Architect. Wall mounted fans 400/450 mm dia. make As specified in tender document or approved by SBI/ Architect. BODY) 	Nos. Nos. Nos.	6.00 2.00 4.00 8.00	
ii iii iv v	 connecting wires etc. all complete as per the directions of Engineer-in-charge (All LED Light Fixures should be covered with minimum 3 Years onsite replacement warranty). FULL GLOW 2 X 2 LED 32 W slim Smart Panel of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 15/18 W LED commercial type down lighter of make As specified in tender document or approved by SBI/ Architect. Supplying, fixing, testing and commissioning of 20 W LED T-5 fitting make As specified in tender document or approved by SBI/ Architect. LED Strip for cove lighting 15 W per 5 M with driver and necessary installation supporting fittings of Led strip light (5 mtr.) make as specified in tender document or approved by SBI/ Architect. Wall mounted fans 400/450 mm dia. make As specified in tender document or approved by SBI/ Architect. BODY) 	Nos. Nos. Nos.	6.00 2.00 4.00 8.00	

1	Supply, Installation, Testing and Commissioning of Maintenace Free Earthing system made up of copper-bonded rod of 10 feet length,23 mm dia. (Minimum copper bonding shall be 0.25mm) along with Rod-to-Conductor connectors, Earth enhancement material, Pit Cover and other accessories as required and as per specification and other applicable codes (include chamber for earthing, Earthing certificate to be submitted along with the bill).	Nos	1.00	
2	Supply, Installation, Testing and Commissioning of Maintenace Free Earthing system made up of copper-bonded rod of 10 feet length, 17.2 mm dia. (Minimum copper bonding shall be 0.25 mm) along with Rod-to-Conductor connectors, Earth enhancement material, Pit Cover and other accessories as required and as per specification and other applicable codes (include chamber for earthing, Earthing certificate to be submitted along with the bill).	Nos	1.00	
3	Providing and fixing of Copper/ GI strips in surface or in recess for loop earthing etc. as required.			
i	Providing and fixing 2 X 8 SWG dia. Cu earth wire in PVC conduit on surface or in recess for loop earthing along with the existing surface/ recess cable as required eith using of copper lug at end termination	RM	80.00	
G.	MAIN PANEL AND METER BOARD			
	supply, installation, testing and commissionings of cubicle type floor/wall mounted L.T. Metal D.B of reputeded make with extendeble rotary handle and extended connecting links			
	1 No. 100 Amps, TPN MCCB (25 KA) with standard enclosure as per manufacturer specification or as approved by the architect/Bank's Engineer	Nos.	1.00	
2	Designing, fabrication, supply, installation, testing and commissionings of front operated cubicle type compartmentalised, front access, free standing on 75MM "[" MS channel, dust and vermin proof (IP 42 degree protection) panel suitable for use at 415V, 3 phase, 4-wire/XLPE Cable 50Hz system suitable for fault level of required value symmetrical at 415V fabricated from 2 mm thick CRCA MS sheets with hinged, gaskettled (Metal based neoprene) locable doors having structural reinforcement including 3 mm thick gland plates on top and bottom, lifting hooks, GI earth strip of required size with 2 nos earth terminals, 1 nos 230V AC operated 250 mm X 250 mm size axial fans for exhaust of heat with On-Off toggle switches including 2 coated primer and 2 power coated paint fnish of approved shade over metal surface cleaned and treated with seven tank process complete with interconnections etc as per specifications as required.main panel board of approved make (Supertech Power Control/Zeniya/Amptech/Neptune) or Equivalent as approved by Architect /Bank.			
	Type of Approval as instructed by the SBI/ Architect). All live accessible parts shall be shrouded and all equipment shall be finger touch proof. The busbars insulation shall be with heat shrinkable sleeves SMC/ DMC shrouds and busbar supports shall be used. Padlocking facility shall be provided on all outgoing feeders doors and switch handles shall be locable in OFF position.			

			1	1		
	Suitable arrangement shall be made for termination of multiple					
	incoming cables.					
	All kA values indicated shall be Ics breaking capacity					
	GA drawings shall be got approved by Architect / SBI					
a.	Floor panel shall consists of : -					
	INCOMER FROM MAIN LINE					
	1 No. 125 Amps, TPN MCCB (25 KA) with					
	extendeble rotary handle each thermal over current,					
	instantaneous, Short circuit realease,Earth fault.					
	BUSBARS					
	150/160 amps TPN pole busbar chamber of suitable					
	length with copper busbars. All busbars and					
	interconnections shall be of suitable size copper					
	strips.					
	INDICATING PANEL					
	Digital flush type class-1.0 accuracy					
	multifunction meter showing V, A, PF etc. with 3 Nos.					
	current transformers of 125/5A ratio, 10 VA					
L	Class-1.0 metering 1 sets					
	Red/Blue/Yellow three phase indicating lamps					
	with SP MCB backup protection.					
	OUTGOINGS:-					
	1 Nos 40A TPN MCCB (16 kA) terminals suitable to					
	receive cable on one side and wire connection to Bus					
	bars For capacitor Bank					
	1 Nos 40A TPN MCCB (16 kA) terminals suitable to					
	receive cable on one side and wire connection to Bus					
	hars For AC VTPN					
b	INCOMER FROM MAIN PANEL BUS BAR					
	1no. 100 Amp 4-P On Load Change over switch					
	with 1 No. 100 Amps, TPN MCCB (25 KA) with extendeble					
	rotary handle.					
	BUSBARS					
	125 amps TPN pole busbar chamber of suitable					
	length with copper busbars. All busbars and					
	interconnections shall be of suitable size copper					
	strips.					
	INDICATING PANEL					
	Digital flush type class-1.0 accuracy					
	multifunction meter showing V, A, PF etc. with 3 Nos.					
	current transformers of 100/5A ratio, 10 VA					
	Class-1.0 metering 1 sets					
	OUTGOINGS:-					
	2 Nos 63A TPN MCB (10 kA) terminals suitable to receive					
	cable on one side and wire connection					
	to Bus bars. (For PDB & UPS)					
	3 Nos 40A TPN MCB (10 kA) terminals suitable to receive cable on one side and wire connection					
	to Bus bars, (For LDB,UPS & Spare)					
	3 Nos 40A DP MCB (10 kA) terminals suitable to					
	receive cable on one side and wire connection to Bus					
	bars. (For ATM & SIGNAGE.SPARE)					
	The electrical panel as described above and specifications	Set	1.00			
	complete.	200				
	complete.					
3	Supply, installation, testing and commissioning of 12 KVAR					
3	capacitor as following-					
	TO SALE AND AND AND AND AND AND A SALE AND A		1		1	

	Incoming- 40A 4pole MCCB, Outgoing- 6 stage power factor relay with 3 nos. 50/5 current transformer for current sensing capasitor 1 KVR- 1 nos, 2 KVR- 3 nos., 5 KVR- 1 nos. Contractors and TP MCB on each complete withphase indication and stage indication. MS cubical having ventilation with wiremesh, copper conductors and aluminium busbars etc complete as per direction of Architect /Bank. (Selec/Neptune/ABB) or Equivalent as approved by Architect /Bank.	Set	1.00		
Н	PUBLIC ADDRESS SYSTEM				
2	Point Wiring of 1.5 sq mm twin core shelded type of speaker cable with Providing and fixing in position the following FRLS PVC conduits including all accessories concealed/exposed in F.Ceiling/Wall complete as required including 1.6/2.0 mm thick PVC junction or pull boxes with 3mm thick perspex sheet cover plate complete with 1.6 mm dia G.I. pull wires in the length of conduit. including all accessaries. Supply, installation, testing and commissioning of following Philips (BOSCH) make Music Accessories / Equipments.	Nos.	5.00		
a.	Ceiling Speaker Unit 6 Watts	Nos.	5.00		
b	Power Amplifier, min 70 Watts with output transformer etc. complete. Plena Range/ Ahuja or as approved by the Bank capable of taking Inputs from USB Also.	Nos.	1.00		